

Technical data

Home power stations of the PRO series All In One



INFINITY

Battery retrofitting
for 5 years



A member of Hager Group

Technical data

S10 E PRO COMPACT Generation

Input

Max. recommended DC power (W)	20,000
Min. MPP voltage (V)	250
Min. MPP voltage for AC rated power (V)	500
Max. MPP voltage (V)	850
Max. DC input voltage (V)	1,000
Max. DC current per MPP tracker (A)	27
Max. PV short-circuit current per MPP tracker (A)	31
Independent MPP trackers	2
Input connection technology	4 x MC4 connectors
Compatibility with module optimisers	Yes
AC storage system – max. input power (W)	All E3/DC home power stations are hybrid storage systems ¹⁾²⁾

Output

Max. AC rated power (230 V, 50 Hz) (W)	12,000 (depending on PV size)
Max. apparent output power (VA)	13,500
AC rated voltage L / N / PE 230 V (V)	3 x 230
AC rated frequencies (Hz)	50
Max. output current (per phase) (A)	20
Feed-in phases / connection phases	3 / 3
Technology	Transformerless
Cos (phi)	-0.9 ... +0.9

General data

Max. system efficiency incl. battery (%)	> 88
EU efficiency of PV power inverter (%)	> 95
AC short-circuit-proof / earth-fault monit.	Yes / yes
Approvals	VDE-AR-N 4105:2018-11, VDE V 0124-100:2020-06, TOR Erzeuger, OVE Guideline R25:2020-03-01, CE, UN38.3, OVE E 8101:2019-01-01
Permissible / recommended ambient temperature (°C)	+5 to +35 / +15 to +25
Max. relative humidity (%)	85
Max. operating altitude (mamsl)	2000
Protection class / cooling	IP20 / fan according to output
Data interface	RS232 / USB / Ethernet / CAN
Dimensions W x H x D (mm)	590 x 1,200 (incl. battery cabinet 1,980) x 500
Display	7" TFT display
Energy management	Integrated

Operating modes

DC operation	Yes
AC storage system	Yes
Backup power supply (rechargeable using solar energy)	Yes ³⁾ (3ph backup power)
Hybrid (DC + AC)	Yes

Technical data

S10 E PRO COMPACT Storage

S10 E PRO COMPACT	19.5	24	30
Usable battery capacity (kWh) ⁴⁾	17.5	23.4	29.2
Number of battery modules	3	4	5
Rated power, charging / discharge (kW) ²⁾	7.5	9 ^{2a)}	9 ^{2a)}
Battery technology	Lithium-ion, certified according to IEC62619		
Total weight of batteries (kg)	Approx. 90	Approx. 135	Approx. 180
E3/DC temperature regulation	Yes		
Maximum extension/retrofitting up to 1 year after installation to (number of modules/kWh usable) ⁵⁾	9 / 52.3		
Maximum INFINITY retrofitting up to 5 years after installation to (number of modules/kWh usable) ^{5) 6)}	9 / 52.3	7 / 40.8	8 / 46.5
Battery capacity warranty ⁷⁾	10 years on 80 % of the usable battery capacity		

Ready for future

System and options	19.5	24	30
Feed-in	Freely selectable between 0 % (non-EEG operation) and 100 %		
Vehicle2Home interface (use of electric car as storage system)	System is compatible with future products ⁸⁾ System is prepared		
Optional overvoltage protection with monitoring	System is prepared		
Ext. interfaces	ModBUS(TCP), KNX, CAN-I/O, xComfort		
Backup power type ³⁾	3ph backup power (home) for light and comfort consumption		
Backup power reserve (adjustable)	Continuously possible on operation with 2 battery sets ⁹⁾		
Max. rated power of battery in backup power (kW) ²⁾ / rechargeable using solar energy (check starting currents / loads)	7.5	9 ^{2a)}	9 ^{2a)}
Backup power operation of motors, pumps and heat pumps ²⁾	Conditionally possible and to be checked with the manufacturer of the inverters / motors as regards starting current and typical, desired power		
SG Ready (for heat pumps, etc.)	SG Ready board (incl.), ModBUS(TCP) (incl.), xComfort actuators (optional)		
Conformity in accordance with §14a of the German Energy Industry Act (EnWG)	EEBus integrated		
Home automation	KNX, myGEKKO, Loxone, xComfort		
Max. system weight without batteries (kg)	145		

The output and the temporal availability of the backup power function can be limited due to software updates, power inverter grid testing and grid conditions and external framework conditions (i.e. home load, generation, hardware defect, temperature, battery calibration). The PRO series has two separate battery sets and can permanently maintain a backup power reserve, although each battery set is also calibrated each week with its own current. Further important information concerning backup power operation can be found in the "Backup power" flyer at e3dc.com/en/infocentre/#Downloads.

¹⁾ The AC charging capacity corresponds to a maximum of the rated power / peak power of the battery system.

²⁾ The actual power is dependent on the state of the system and the temperature, and can be lower depending on the PV and weather / grid conditions.

^{2a)} On connection of at least two modules per battery circuit.

³⁾ Additional motor switch required for the backup power function subject to a surcharge. Consumers with non-sinusoidal and excessively high power must be shut off if necessary.

⁴⁾ The warranty refers to 80 % of this usable capacity.

⁵⁾ Depending on availability and the battery technology used; equipment and installation space check necessary; not guaranteed. An additional battery cabinet is required as of 6 battery modules. The maximum number of 9 modules is only possible with a second COMPACT battery cabinet.

⁶⁾ In the event of INFINITY retrofitting, the existing battery modules must be connected to a battery tracker. It may be necessary to distribute battery circuit 1 (maximum of 6 modules) to the internal and the external battery cabinet. A maximum of 3 modules can be assigned to the 2nd battery circuit.

⁷⁾ Within the warranty period on adherence to the warranty conditions.

⁸⁾ V2H option is not a legal entitlement of the customer. It is specifically dependent on future vehicles, interfaces / grid guidelines and regulations.

⁹⁾ Physically realised through the design of the PRO system. Independent of battery management.

The service life of the batteries is dependent on the installation and operating conditions. The terms and conditions of HagerEnergy GmbH apply. Internet connection required for remote maintenance and checking the yield.

ENERGY STORAGE E3 DC

HagerEnergy GmbH
Ursula-Flick-Strasse 8
D-49076 Osnabrück

P +49 541 760 268 0

     [e3dc.com](https://www.e3dc.com)

Your E3/DC partner



+ Wallbox
+ Inverter
+ HEMS